



PB XA LED DISPLAY

Model	XA3	XA4	XA5	XA6
Pixel Pitch	3	4	5	6
Module Dimension (W x H) (mm)	192 x 192	240 x 180		
Cabinet Dimension (W x H) (mm)	768 x 768	960 x 720		
Cabinet Weight (kg / m ²)	45			
Serviceability	Rear			
IP Rating (Front/ Rear)	65 / 54			
Cabinet Material	Aluminium			
Brightness (Nits)	4500	5500		
Viewing Angle (H)	160°			
Viewing Angle (V)	70°			
Refresh Rate (Hz)	3840			
Brightness Level (Manual / Auto / Time) (%)	0 ~ 100			
Color Temperature (Adjustable) (K)	3200 ~ 9500			
Input Voltage (VAC)	85 ~ 265			
Operating Temperature	-20 ~ 60°			
Storage Temperature	-40 ~ 60°			
Operating Humidity (RH) (%)	5 ~ 95			
Storage Humidity (RH) (%)	5 ~ 95			
LED Lifetime (hrs)	100.000			
Max.power consumption (W/m ²)	1000			
Avg.power consumption (W/m ²)	250			
Warranty	2 years			

* Parameters above are typical values, which may be adjusted according to actual project requirements.

MODULE XA



**SIMPLE
INSTALLATION**



**EASY-TO-CONNECT
(PLUG-IN SYSTEM)**



**FRONT
MAINTENANCE**



**SMART
CONNECTION
(CONTROL SYSTEM)**

ASK PHILIPP!

+49 421 83570130
kontakt@pixelbeast.de
www.pixelbeast.de



- Flexible usage
- High contrast and high clarity
- Wall-mounting or stand-alone-mounting available
- Perfect heat control
- Long lifetime



- **High Contrast Ratio:**

Entire Black package SMD, more than 3000:1 contrast ratio, clearer and more natural image displaying.

- **Multifunctional Module Buckle Design:**

Easily adjusting gaps between module and cabinet, ensuring smoothness and alignment of LED face.

- **Intelligent Software System:**

Intelligent control and player system by cloud technology. Timely managing real-time information on operating status and potential fault.

- **Independent Internal Connection:**

Independent connection between control board and modules. Single module failure not impacting others.

- **Unique CPU Processing Technology:**

Automatically saving calibration data, not needing to re-adjust after replacing the module. Automatically detecting operating status, fault location and any potential risks.

ASK PHILIPP!

+49 421 83570130

kontakt@pixxelbeast.de

www.pixxelbeast.de



Safety:

- The product is conductive - please keep away from power sources!
- Installation and maintenance may only be carried out by qualified electricians!
- Switch off the display by technical difficulties!
- Don't touch without gloves!



Cleaning:

- Do not clean the display with water
- Do not clean the display directly with a cleaning rag
- Clean dry and carefully